

```

!
version 12.3
no service pad
service timestamps debug datetime msec
service timestamps log datetime msec
service password-encryption
!
hostname TSE-AP-CISCO
!
enable secret 5 $1$ElTM$Iyla7JBKKyQJrf3cv7yUz1
!
ip subnet-zero
ip domain name tse.com
ip name-server 192.168.30.1
!
!
no aaa new-model
dot11 vlan-name Firmenleitung vlan 20
dot11 vlan-name Firmennetzwerk vlan 10
dot11 vlan-name Netzwerkverwaltung vlan 99
dot11 vlan-name Server vlan 30
!
dot11 ssid TSE-AP-02-VLAN10
    vlan 10
    authentication open
    authentication key-management wpa optional
    mbssid guest-mode
    wpa-psk ascii 7 00300023411F59565E73
!
dot11 ssid TSE-AP-02-VLAN20
    vlan 20
    authentication open
    authentication key-management wpa optional
    mbssid guest-mode
    wpa-psk ascii 7 053F152A64081C594857
!
!
!
username Cisco password 7 13261E010803
!
bridge irb
!
!
interface Dot11Radio0
    no ip address
    no ip route-cache
!
    encryption mode ciphers aes-ccm tkip wep128
!
    encryption vlan 10 mode ciphers aes-ccm tkip wep128
!
    encryption vlan 99 mode ciphers aes-ccm tkip wep128
!
    encryption vlan 20 mode ciphers aes-ccm tkip wep128
!
ssid TSE-AP-02-VLAN10
!
ssid TSE-AP-02-VLAN20
!
mbssid
    speed basic-1.0 basic-2.0 basic-5.5 basic-6.0 basic-9.0 basic-11.0
    basic-12.0 basic-18.0 basic-24.0 basic-36.0 basic-48.0 basic-54.0
    power local cck 1
    power local ofdm 1
    no power client local

```

```
power client 1
station-role root
!
interface Dot11Radio0.10
  encapsulation dot1Q 10
  no ip route-cache
  bridge-group 10
    bridge-group 10 subscriber-loop-control
    bridge-group 10 block-unknown-source
    no bridge-group 10 source-learning
    no bridge-group 10 unicast-flooding
    bridge-group 10 spanning-disabled
!
interface Dot11Radio0.20
  encapsulation dot1Q 20
  no ip route-cache
  bridge-group 20
    bridge-group 20 subscriber-loop-control
    bridge-group 20 block-unknown-source
    no bridge-group 20 source-learning
    no bridge-group 20 unicast-flooding
    bridge-group 20 spanning-disabled
!
interface Dot11Radio0.30
  encapsulation dot1Q 30
  no ip route-cache
  bridge-group 30
    bridge-group 30 subscriber-loop-control
    bridge-group 30 block-unknown-source
    no bridge-group 30 source-learning
    no bridge-group 30 unicast-flooding
    bridge-group 30 spanning-disabled
!
interface Dot11Radio0.99
  encapsulation dot1Q 99 native
  no ip route-cache
  bridge-group 1
    bridge-group 1 subscriber-loop-control
    bridge-group 1 block-unknown-source
    no bridge-group 1 source-learning
    no bridge-group 1 unicast-flooding
    bridge-group 1 spanning-disabled
!
interface FastEthernet0
  no ip address
  no ip route-cache
  duplex auto
  speed auto
  hold-queue 160 in
!
interface FastEthernet0.10
  encapsulation dot1Q 10
  no ip route-cache
  bridge-group 10
    no bridge-group 10 source-learning
    bridge-group 10 spanning-disabled
!
interface FastEthernet0.20
  encapsulation dot1Q 20
  no ip route-cache
  bridge-group 20
    no bridge-group 20 source-learning
    bridge-group 20 spanning-disabled
!
interface FastEthernet0.30
  encapsulation dot1Q 30
```

```
no ip route-cache
bridge-group 30
no bridge-group 30 source-learning
bridge-group 30 spanning-disabled
!
interface FastEthernet0.99
  encapsulation dot1Q 99 native
  no ip route-cache
  bridge-group 1
  no bridge-group 1 source-learning
  bridge-group 1 spanning-disabled
!
interface BVI1
  ip address 192.168.99.5 255.255.255.0
  no ip route-cache
!
ip default-gateway 192.168.99.1
no ip http server
ip http secure-server
ip http help-path
http://www.cisco.com/warp/public/779/smbiz/prodconfig/help/eag
!
access-list 111 permit tcp any any neq telnet
!
control-plane
!
bridge 1 route ip
!
!
wlccp ap username Cisco password 7 096F471A1A0A
!
line con 0
  access-class 111 in
line vty 0 4
  access-class 111 in
  login local
!
end
```